


## Coaxial PCB Connector: BMMA-JHD005

### Description

BMMA Male PCB Edge Launch Connector

Interface Standards:

P/N: 005-BM110N-NS



### Technical Data

#### Electrical Data

Impedance	50 $\Omega$
Interface frequency max.	26.5 GHz
VSWR	1.45 MAX(@ 18 GHz)
Insertion Loss	0.15XSQRT[F(GHz) ]dB MAX

#### Mechanical Data

Number of matings 500

#### Size

Length	12.65 mm
Width	6.35 mm
Height	7.65 mm

#### Environmental Data

Operating Temperature	-65°C to 165°C
RoHS	Compliant

#### Material Data

Centre contact	Beryllium Copper	Gold Plating
Outer contact	Beryllium Copper	Gold Plating
Body	Brass	Gold Plating
Insulator	PTFE	

### Drawing

